## **D3220Ph-Nd**

## Professional Compression Driver




## **KEY FEATURES**


- · 3" Voice coil and 2" exit
- · 110 Watts continuous power handling
- · 109 dB Sensitivity
- · Phenolic Diaphragm
- · Light Weight Neodymium Magnet

Exit Throat Diameter	2" (50 mm)
Nominal Impedance	8 Ohms
Rated Power Handling	110 Watts
Program Power	220Watts
Sensitivity 2.83V at 1m*	110 dB
Recommended High Pass Crossover**  **for Full Power Handling	800 Hz*** ***12 db/oct Crossover
Frequency Response at -10dB	600 - 7,500Hz
Frequency Response at -10dB  Voice Coil Diameter	<b>600 - 7,500Hz</b> 3" (76.2 mm)
. , .	-
Voice Coil Diameter	3" (76.2 mm)
Voice Coil Diameter Voice Coil Wire	3" (76.2 mm) Cooper
Voice Coil Diameter Voice Coil Wire Voice Coil Former Material	3" (76.2 mm) Cooper Kapton <sup>®</sup>


Overal Diameter	4.88" (124 mm)
Overal Depth	2.21" (56 mm)
Mounting Bolt Circle	M6 x 4 4" (101.6 mm)
Net Weight	4.72 lbs (2.14 kg)
Shipping Weight	4.99 lbs (2.26 kg)
Carton Dimensions W x L x H	5.71" x 5.71" x 3.35" (145 x 145 x 85 mm)







## Frequency Response Measured at 2.83v/1m



\*Frequency Response Measured on WG14-50CR

PRV AUDIO USA (USA and Export) PRV AUDIO BRAZIL (Brazilian Sales Only)
POMPANO BEACH, FL SAO LEOPOLDO, RS
support@prvaudio.com vendas@pvaudio.com.br
www.prvaudio.com